

Aurora UPS

Reliable Power Protection with standard battery backup



The Eaton Aurora Line-Interactive UPS affordably protects critical applications from downtime, data loss and corruption caused by power fluctuations and outages.

With built-in Double Boost and Buck Automatic Voltage Regulation, the Aurora is perfect for areas where the supply voltage is constantly unstable.

Designed for IT applications requiring standard power backup time, the Aurora features a microprocessor controller for managing power.

Product Snapshot

Power Rating	: 600/1000 VA
Configuration	: Tower
Voltage	: 230V
Frequency	: 50 Hz
Technology	: High-frequency line-interactive

Features

- Microprocessor controller design assures maximum reliability and stability
- Double Boost & Buck voltage regulation provides stabilised output
- Stepped sine wave provides high efficiency
- Wide input-voltage range appropriate for the harshest electrical environments
- Up to 4 India type 5A output receptacles
- Auto-restart function
- Cold start on battery power allows portable power
- Compact design is perfect for placement on or under a desk
- Green Power function prevents battery discharge when no load is present

Line-Interactive topology

This topology guarantees consistent reliability and high level of power quality. Whatever the supply disturbances, the output waveform is stabilised via double boost and buck mode. The battery is used only as a backup source.

High performance and reliability

Aurora features a microprocessor controller that delivers modified sine wave output offering the highest levels of reliability and efficiency, all in a compact design.

Wide Input-voltage range

Aurora has a very wide input voltage range of 140-300V, which reduces the number of transfers to battery power.

Cold start on battery power

This function ensures trouble free start-up of your applications even during a utility power outage.

Auto restart function

When AC power returns the UPS will automatically restart without user intervention.

Overload protection

Alerts the user and prevents the UPS from being damaged.



Powering Business Worldwide

Technical Specifications

Model : VA/Watts	600VA/360W	1000VA/600W
Technology	Line - Interactive with Microprocessor Controlled Design	
Input / Output		
Nominal Input Voltage	230Vac 1 Phase	
Input Voltage Window @ full load	140 - 300Vac (load dependent)	
Input Power Factor	0.98	
Frequency & Frequency Range	50+/- 1Hz	
Nominal Output Voltage	230V	
Output Voltage on Battery	+10 % / -10%	
Output Waveform	Modified sine wave	
Input Connection	C14 5A	
Output Receptacles	(3) IN 5A	(4) IN 5A
Battery		
Battery Quantity	1 x 12V/7AH x 1	1 x 12V/7AH x 2
Re-charge Time to 90% Capacity	6 hours	
Battery Backup Time* (At a PC load with 15" monitor)	15-20 minutes	30-35 minutes
Start-on-Battery	UPS can be started without being connected to AC utility power	
Communication	RS232 Port	
User Interface		
Visual	Line Mode: Green LED Lighting Battery Mode: Green LED Flashing Fault: None	Line Mode: Green LED Lighting Battery Mode: Yellow LED Flashing Fault: Red LED Lighting
Control	One button for On/Off	
Environment		
Operating Temperature	0°C ~ 40°C	
Storage Temperature	-15°C ~ 50°C	
Humidity	0 ~ 90%	
Noise Level	<40dB	
Dimensions & Weights W x H x D mm		
Models (W x H x D) mm	278 x 100 x 143	364 x 139 x 195
Gross Weight (kg)	5.4	10.43

In the interest of continuous product improvement, all specifications are subject to change without notice.

*Battery backup times are approximate and may vary with equipment, configuration, battery age, temperature, etc.



South Asia Office

Eaton's Electrical Sector
Eaton Power Quality Pvt. Ltd.
2, EVR Street, Sedarpet Industrial Estate,
Pondicherry - 605 111. Tel: +91 413 2672000
Sales and Service
Toll Free Hotline: 1800 425 7585
E-mail: EatonPowerQualityIndia@eaton.com

Offices Across India

New Delhi
Unit A1 & B1, 3rd Floor,
TDI Centre, Plot No. - 7, Jasola,
New Delhi - 110025
Ph: 011 45851800

Mumbai
EL Floor, VITS Luxury Business Hotel,
Andheri Kurla Road, Andheri (East),
Mumbai - 400 059
Tel : +91 22 4005 3817
Fax: +91 22 4005 3810

Bangalore
Unit No. 501, 4th Floor,
Prestige Atrium, Central Street,
Bangalore - 560 001
Tel : +91 80 4901 2200
Fax: +91 80 4901 2239

Hyderabad
Ground and First Floor,
8-3-1110/B/2, Plot No.104,
Keshav Nagar Colony,
Srinagar Colony post.
Hyderabad - 500 073
Tel : +91 40 4018 9601

Chennai
No. 36, Nehru Street,
Off. Old Mahabalipuram
Road, Sholinganallur,
Chennai - 600 019

Ahmedabad +91 8980040323
Chandigarh +91 9356856675
Coimbatore +91 9344067649
Cochin +91 9344067649
Gurgaon +91 9312051030
Kolkata +91 33 4004 0968
Pune +91 9325052902

Sales and Service Operations

Sri Lanka
+94 11 2871 000, 7520 000
+94 11 7520 031

Nepal
+97 714429777, 714429888
+97 714423376

Bangladesh
+8802 7170368, 7162568, 7162619
+8802 9347918, 9330765, 9348220
+8802 9130363, 9139314